





Size: 20.5x12.4x14.5 (LxWxH)

Rated voltage: 250V  
Rated current: 32A  
Rated impulse voltage: 4KV  
Solid size: 0.08-2.5mm<sup>2</sup>  
Multi-folded yarn size: 0.08-4mm<sup>2</sup>  
Strip length:  10mm





Size: 20.5x17.2x14.5 (LxWxH)

Rated voltage: 250V  
Rated current: 32A  
Rated impulse voltage: 4KV  
Solid size: 0.08-2.5mm<sup>2</sup>  
Multi-folded yarn size: 0.08-4mm<sup>2</sup>  
Strip length:  10mm




Size: 20.5x22.4x14.5 (LxWxH)

Rated voltage: 250V  
Rated current: 32A  
Rated impulse voltage: 4KV  
Solid size: 0.08-2.5mm<sup>2</sup>  
Multi-folded yarn size: 0.08-4mm<sup>2</sup>  
Strip length:  10mm



Size: 20.5x26.6x14.5 (LxWxH)

Rated voltage: 250V  
Rated current: 32A  
Rated impulse voltage: 4KV  
Solid size: 0.08-2.5mm<sup>2</sup>  
Multi-folded yarn size: 0.08-4mm<sup>2</sup>  
Strip length:  10mm

Dimension ± 0.5mm

## Usage method



## Using Scenes



How to use:

1.Strip wire insulation 9-10mm long.

2.Push the lever to open the line hole, insert the wire, push the lever to its closed position.



Strip wire 9 – 10 mm



Push up lever and insert conductor



lower the lever to its closed position



0.08 - 2.5 mm<sup>2</sup>  
28 - 14 AWG



0.08 - 4 mm<sup>2</sup>  
28 - 12 AWG



0.08 - 4 mm<sup>2</sup>  
28 - 12 AWG