

Surge Arrester T23-A230XF4

3-Electrode-Arrester

Ordering code: B88069X8750B502

DC spark-over voltage 1) 2) 3)	230	V
	± 20	%
Impulse spark-over voltage 3)		
at 100 V/µs - for 99 % of measured values	< 400	V
 typical values of distribution 	< 350	V
at 1 kV/µs - for 99 % of measured values	< 500	V
- typical values of distribution	< 450	V
Service life		
10 operations 50 Hz, 1 s ⁴⁾	10	Α
1 operations 50 Hz, 0.18 s (9 cycles) 4)	50	Α
10 operations 8/20 µs ⁴⁾	20	kA
1 operation 8/20 µs ⁴⁾	25	kA
300 operations 10/1000 μs ⁴⁾	200	А
Response time of failsafe mechanism		
at 1 A, typical	< 10	s
Insulation resistance at 100 V _{dc} ³⁾	> 10	GΩ
Capacitance at 1 MHz ³⁾	< 1.5	pF
Transverse delay time	< 0.2	μs
Arc voltage at 1 A, typical	< 25	V
Glow to arc transition current	~ 1	Α
Glow voltage	~ 200	V
Weight	~ 2.2	g
Storage temperature	-40 +90	°C
Climatic category (IEC 60068-1)	40/ 90/ 21	
Marking, blue	EPCOS 230 YY O 230 - Nominal voltage YY - Year of production O - Non radioactive	

¹⁾ At delivery AQL 0.65 level II, DIN ISO 2859

Terms and tests in accordance with ITU-T Rec. K.12 and DIN 57845/VDE0845

The arrester failsafe mechanism contains a solder pellet with a melting temperature between 193 and 203 $^{\circ}$ C.

AB E / AB PM Issue 07, 21.04.2004

²⁾ In ionized mode

Tip or ring electrode to center electrode


Total current through center electrode, half value through tip respectively ring electrode.



Surge Arrester T23-A230XF4

3-Electrode-Arrester

Ordering code: B88069X8750B502



Not to scale

Dimensions in mm

Non controlled document

AB E / AB PM Issue 07, 21.04.2004

[©] EPCOS AG 2002. Reproduction, publication and dissemination of this data sheet, enclosures hereto and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.